(1)

Sampling & quantization

$f(x,y)$ = Image

Sampling : the process of digitizing the spatial coordinates (x,y)



Quantization : the process of digitizing the amplitude (intensity level) values.

0 1 2 3 4 - .. 255

Image Representation

- Surface (3-D image)

  image where two dimension represent spitual coordinates (x,y) and the third dimension is the intensity level.

- Image for human

  2-D image



used by human to see objects.

- Array images

  the image is represented as matrix of f values (used in algorithms)

- k-bit image

bit k لكل pixel



$L = 2^K$: no. of intensity levels.

مثلا e.g 8-bit $\Rightarrow$ 256 Level

Dynamic Range = $\frac{\text{Max intensity Level}}{\text{Min intensity Level}}$

Contrast = Max intensity Level − Min intensity Level

ماذا يؤثر على الصورة؟

Max intensity is Controlled by Saturation

Min intensity Level is Controlled by noise

Image Storage

$b = M \times N \times K$

- b: Storage of image by bits
- K: no. of bits for each pixel



patial resolution no. of pixels per unit distance. (DPI)

Intensity resolution: no. of bits used to quantize intensity.

no. intensity = 2^K

Interpolation: is the process of using Known data to estimate values of unknown Location

Resizing تغيير حجم الصور



Types of interpolation:

① nearest neighbor interpolation

it assigns to each new Location the intensity of its nearest neighbor in the orginal image.

produce Bad results (pixeled images)

② bilinear :

Use the 4 nearest neighbors to estimate the intensity at agiven Location

give better results

③ bicubic which involves the 16 nearest neighbor of a point.

Best results

neighborhood & adjacency



$N_4(p) = \{x, y, z, w\}$ الجيران الرأسي الرأسي





$N_D(p) = \{x, y, z, w\}$ الجيران القطريين

Diagonal قطر

$N_8(p) = N_4(p) \cup N_D(p)$ الجيران الكلي



$V = \{5, 6, 10\}$

List of intensity

$N_m(p) \Rightarrow N_4(p) \Rightarrow x \in V, m(p)$

or $\Rightarrow N_D(p)$ iff $N_4(p) \cap N_4(q) = \phi$

Sensors to Capture (التقاط) Images

1) Single Sensor

both x & y dimension are controlled by Mechanical movement.

2) Sensor Strip

- one dimension is controlled by mechanical Movement
- the other direction is controlled by the no. of sensors on the strip.

3) Sensor Array



- no mechanical Movement

Image Acquisition

1 Single Sensor



both x & y dimension is controlled by mechanical movement.

2 Sensor Strip



- one dimension is controlled by the number of sensors
- and the other dimension is controlled by mechanical movement.

3 Array Sensor



- No mechanical Movement
- two dimensions of image are controlled by number of pixels in the 2-D array.